TS-710 SYSTEM

TS-710 - GBATS CORE FUNCTIONAL TEST SYSTEM

- Preconfigured, cost effective, basic functional test platform for general purpose test / ATE applications
- •Integral, high density interface
- •Compact platform ideal for bench top test configurations
- •PXI architecture accommodates both 3U and 6U modules
- •Wide selection of standard options minimizes delivery time and costs



DESCRIPTION

The TS-710 GBATS (Geotest Basic Test System) is a preconfigured, modular test platform which provides basic functional test / ATE capability for production, depot, and repair facilities. Based on Geotest's GX7102A PXI platform, the TS-710 platform offers test engineers a preconfigured, compact, 3U / 6U system which can also be enhanced with a variety of options for supporting complex analog, digital, and mixed-signal test applications. The system comes with a high pin count, cabled interface – making it ideal for supporting box level products such as LRU, sub-system assemblies, and system level assemblies. The TS-710 platform is also available with Geotest's ATEasy software, which provides an integrated and complete test executive and test development environment, allowing users to quickly develop and easily maintain test applications.

FEATURES

The TS-710 consists of a preconfigured, core system which provides the basic infrastructure for testing analog / digital devices or systems. The system includes user power, switching, and basic analog / digital instrumentation.

TS-710 CORE SYSTEM CONFIGURATION

The core system includes the following test resources and capabilities:

- •GX7102A 14-slot, PXI chassis with (6) 6U and (7) 3U peripheral slots
- 960 pin, high density, zero insertion force, iCON style UUT interface providing access to all core and optional system resources
- •GX7920 Embedded controller with Windows XP
- Analog / Digital PMC module: 8 general purpose differential analog inputs, 4 analog outputs, and 8 adapter ID inputs
- •GX6377, multi-function relay / matrix card

- GX7404, power interface & prototype card
- •SMX2040 6.5 digit DMM
- GX5733, 128 channel digital I/O card
- (3) 3U and (6) 6U PXI slots for additional system resources

TS-710 DIGITAL OPTIONS

Both static and dynamic digital test instrumentation is supported by the TS-710 platform. Digital instrumentation options include:

- •GX5280 or GX5290 series digital cards, supporting vector rates up to 200 MHz and up to 96 channels
- GX5733 a high density, static I/O card, supporting up to 128 digital I/O channels

TS-710 ANALOG AND SWITCHING OPTIONS

Analog source, measure, and switching options for the TS-710 system include:

- •GX1110 Arbitrary Waveform Function Generator
- •GX2472 Dual Channel Digitizer
- •GTX2200 series Counter / Timer
- •GX1838 precision multi-channel DC source
- •GX7400A dual output, programmable power supply
- •GX6616 high density matrix card
- •Gx6315 high current relay card
- •GX6384 switch matrix (replaces GX6377)

The TS-710's UUT interface employs a unique design approach which allows customization of the system using any of the described instrument options, without incurring the cost and design time typically associated with a customized functional test system. The resulting benefit for the end user is a test system that is cost effective and easily configured for a specific application(s), using



TS-710 SYSTEM

off the shelf components and modules. In addition, an additional (optional) iCON interface connector can be installed, providing additional interconnects to other system resources within the PXI chassis or to external resources such as GPIB instrumentation. This connector can be configured for power, signal or coaxial connections – providing the user with a range of options for supporting additional types of instrumentation.

SYSTEM SELF-TEST

The TS-710 is delivered with a system self test which includes an interactive self-test software procedure as well as a self-test adapter. The self-test verifies functional integrity of the system and resource connections to the test system interface.

APPLICATIONS

- •LRU, sub-system and system level functional test
- Production test or repair of modules and systems
- •Bench top ATE

SPECIFICATIONS

MAINFRAME ELECTRICAL & MECHANICAL	
MAINFRAME	GX7102A 6U / 3U PXI chassis
	(6) 6U & (7) 3U peripheral slots
SYSTEM CPU (EMBEDDED)	Pentium®M 1.4 GHz , single slot 6U
	Core 2 Duo, 216 GHz – single slot 6U
	, optiona
CPU MEMORY	1 GB
	2 GB - optional
SYSTEM HARD DISK	160 GB
SYSTEM PERIPHERALS	Floppy & DVD-RW drives
CPU INTERFACES	RS-232, USB, 10-Base T,
	100BaseT, 1000BaseT, PS2, VGA
UUT INTERFACE	Virginia Panel iCON, 960 pin interface
	Additional 220 pin interface available
	(option)
INPUT POWER	120 / 240 VAC, 20 A, 50/60 Hz

ANALOG / DIGITAL PMC RESOURCE MODULE		
GENERAL PURPOSE ANALOG INPUTS	8, differential inputs, 16 bit resolution	
	Input impedance: 1 M ohm	
	+/- 2.5V, +/-5V, or +/- 10 V full scale	
	Aggregate conversion rate: 300KS/s, max	
	DC accuracy:	
	+/- 4.2 mV, 10 volt range	
	+/- 2.8 mV, 5 volt range	
	+/- 2.0 mV, 2.5 volt range	
GENERAL PURPOSE ANALOG OUTPUTS	4, single ended, 16 bit resolution	
	+/- 2.5V, +/-5V, or +/- 10 V full scale	
	Load: 3 ma max. per channel	
	Generate arbitrary and function wave-	
	forms	
	Sample rate: 400 to 300 KS/s per channel	
	DC accuracy:	
	+/- 3.0 mV, 10 volt range	
	+/- 2.2 mV, 5 volt range	
	+/- 1.7 mV, 2.5 volt range	
DIGITAL I/O (CAN BE USED FOR FIXTURE	8 bit, TTL compatible	
ID FUNCTIONALITY)	Configurable as inputs or outputs (byte-	
	wise)	
	Sink / source: 20 mA per line	
INSTRUMENTATION RESOURCES		
	T .	
DIGITAL MULTIMETER	SMX 2040, 6.5 digit DMM	
DIGITAL MULTIMETER SWITCHING	SMX 2040, 6.5 digit DMM GX6377, multi-function relay card. In-	
	GX6377, multi-function relay card. In-	
	GX6377, multi-function relay card. Includes dual 16x2 relay matrix, (5) 10 amp	
	GX6377, multi-function relay card. Includes dual 16x2 relay matrix, (5) 10 amp Form A relays, (4) 2 amp Form A relays,	
SWITCHING	GX6377, multi-function relay card. Includes dual 16x2 relay matrix, (5) 10 amp Form A relays, (4) 2 amp Form A relays, and (4) 2 amp Form C relays.	
SWITCHING	GX6377, multi-function relay card. Includes dual 16x2 relay matrix, (5) 10 amp Form A relays, (4) 2 amp Form A relays, and (4) 2 amp Form C relays. GX7404,power interface and prototype	
SWITCHING	GX6377, multi-function relay card. Includes dual 16x2 relay matrix, (5) 10 amp Form A relays, (4) 2 amp Form A relays, and (4) 2 amp Form C relays. GX7404,power interface and prototype card. Four switched, DC power outputs:	
SWITCHING	GX6377, multi-function relay card. Includes dual 16x2 relay matrix, (5) 10 amp Form A relays, (4) 2 amp Form A relays, and (4) 2 amp Form C relays. GX7404,power interface and prototype card. Four switched, DC power outputs: +3.3V, +5V, +12V, -12V. On-board proto-	
SWITCHING USER POWER	GX6377, multi-function relay card. Includes dual 16x2 relay matrix, (5) 10 amp Form A relays, (4) 2 amp Form A relays, and (4) 2 amp Form C relays. GX7404,power interface and prototype card. Four switched, DC power outputs: +3.3V, +5V, +12V, -12V. On-board prototyping area for custom circuitry.	
SWITCHING USER POWER	GX6377, multi-function relay card. Includes dual 16x2 relay matrix, (5) 10 amp Form A relays, (4) 2 amp Form A relays, and (4) 2 amp Form C relays. GX7404,power interface and prototype card. Four switched, DC power outputs: +3.3V, +5V, +12V, -12V. On-board prototyping area for custom circuitry. GX5733. 128 channel digital I/O card. 96	
SWITCHING USER POWER	GX6377, multi-function relay card. Includes dual 16x2 relay matrix, (5) 10 amp Form A relays, (4) 2 amp Form A relays, and (4) 2 amp Form C relays. GX7404,power interface and prototype card. Four switched, DC power outputs: +3.3V, +5V, +12V, -12V. On-board prototyping area for custom circuitry. GX5733. 128 channel digital I/O card. 96 LVTTL digital channels. 32 bit configurable	
SWITCHING USER POWER	GX6377, multi-function relay card. Includes dual 16x2 relay matrix, (5) 10 amp Form A relays, (4) 2 amp Form A relays, and (4) 2 amp Form C relays. GX7404,power interface and prototype card. Four switched, DC power outputs: +3.3V, +5V, +12V, -12V. On-board prototyping area for custom circuitry. GX5733. 128 channel digital I/O card. 96 LVTTL digital channels. 32 bit configurable port accepts one GX5733 I/O module for	
SWITCHING USER POWER	GX6377, multi-function relay card. Includes dual 16x2 relay matrix, (5) 10 amp Form A relays, (4) 2 amp Form A relays, and (4) 2 amp Form C relays. GX7404,power interface and prototype card. Four switched, DC power outputs: +3.3V, +5V, +12V, -12V. On-board prototyping area for custom circuitry. GX5733. 128 channel digital I/O card. 96 LVTTL digital channels. 32 bit configurable port accepts one GX5733 I/O module for	
SWITCHING USER POWER DIGITAL I/O ENVIRONMENTAL	GX6377, multi-function relay card. Includes dual 16x2 relay matrix, (5) 10 amp Form A relays, (4) 2 amp Form A relays, and (4) 2 amp Form C relays. GX7404,power interface and prototype card. Four switched, DC power outputs: +3.3V, +5V, +12V, -12V. On-board prototyping area for custom circuitry. GX5733. 128 channel digital I/O card. 96 LVTTL digital channels. 32 bit configurable port accepts one GX5733 I/O module for customized input / output levels	
SWITCHING USER POWER DIGITAL I/O ENVIRONMENTAL OPERATING TEMPERATURE	GX6377, multi-function relay card. Includes dual 16x2 relay matrix, (5) 10 amp Form A relays, (4) 2 amp Form A relays, and (4) 2 amp Form C relays. GX7404,power interface and prototype card. Four switched, DC power outputs: +3.3V, +5V, +12V, -12V. On-board prototyping area for custom circuitry. GX5733. 128 channel digital I/O card. 96 LVTTL digital channels. 32 bit configurable port accepts one GX5733 I/O module for customized input / output levels	
SWITCHING USER POWER DIGITAL I/O ENVIRONMENTAL OPERATING TEMPERATURE STORAGE TEMPERATURE	GX6377, multi-function relay card. Includes dual 16x2 relay matrix, (5) 10 amp Form A relays, (4) 2 amp Form A relays, and (4) 2 amp Form C relays. GX7404,power interface and prototype card. Four switched, DC power outputs: +3.3V, +5V, +12V, -12V. On-board prototyping area for custom circuitry. GX5733. 128 channel digital I/O card. 96 LVTTL digital channels. 32 bit configurable port accepts one GX5733 I/O module for customized input / output levels 0° C to 50° C -20° C to 60° C	
SWITCHING USER POWER DIGITAL I/O ENVIRONMENTAL OPERATING TEMPERATURE STORAGE TEMPERATURE RELATIVE HUMIDITY	GX6377, multi-function relay card. Includes dual 16x2 relay matrix, (5) 10 amp Form A relays, (4) 2 amp Form A relays, and (4) 2 amp Form C relays. GX7404,power interface and prototype card. Four switched, DC power outputs: +3.3V, +5V, +12V, -12V. On-board prototyping area for custom circuitry. GX5733. 128 channel digital I/O card. 96 LVTTL digital channels. 32 bit configurable port accepts one GX5733 I/O module for customized input / output levels 0° C to 50° C -20° C to 60° C	
SWITCHING USER POWER DIGITAL I/O ENVIRONMENTAL OPERATING TEMPERATURE STORAGE TEMPERATURE RELATIVE HUMIDITY ALTITUDE	GX6377, multi-function relay card. Includes dual 16x2 relay matrix, (5) 10 amp Form A relays, (4) 2 amp Form A relays, and (4) 2 amp Form C relays. GX7404,power interface and prototype card. Four switched, DC power outputs: +3.3V, +5V, +12V, -12V. On-board prototyping area for custom circuitry. GX5733. 128 channel digital I/O card. 96 LVTTL digital channels. 32 bit configurable port accepts one GX5733 I/O module for customized input / output levels 0° C to 50° C -20° C to 60° C 90%, non-condensing 30,000 ft	
SWITCHING USER POWER DIGITAL I/O ENVIRONMENTAL OPERATING TEMPERATURE STORAGE TEMPERATURE RELATIVE HUMIDITY	GX6377, multi-function relay card. Includes dual 16x2 relay matrix, (5) 10 amp Form A relays, (4) 2 amp Form A relays, and (4) 2 amp Form C relays. GX7404,power interface and prototype card. Four switched, DC power outputs: +3.3V, +5V, +12V, -12V. On-board prototyping area for custom circuitry. GX5733. 128 channel digital I/O card. 96 LVTTL digital channels. 32 bit configurable port accepts one GX5733 I/O module for customized input / output levels 0° C to 50° C -20° C to 60° C	

ORDERING INFORMATION

TS-710	Core Functional Test System
OPTIONS	Contact factory for specific options / configurations

